

>



Model Number: GPE-75EH-1-1

Gillette Generator GPE-75EH-1-1 Industrial Portable Generator 7500 watts 120/240 volts 56/28 Cont Amp Honda GX390 13HP 1 Phase

Manufacturer: Gillette Generator

Gillette Generator GPE-75EH-1-1 Industrial Portable Generator 7500 watts 120/240 volts 56/28 Cont Amp Honda GX390 13HP
Factory Brochure

GENERATOR MODEL

GPE-75EH

MAX. KW @ 1 PH.
7.5

PRIME KW @ 1 PH.
6.5

PRIME AMPS @ 120 V.
54

PRIME AMPS @ 240 V.
27

GENERATOR REGULATION

5 % VOLTAGE REGULATION ON SINGLE PHASE GEN-SETS.

FREQUENCY REGULATION

5 %, (3 HERTZ) FREQUENCY REGULATION FROM NAME PLATE RATING

“KLEEN-POWER”
ELECTRICAL WAVEFORM DISTORTION IS LIMITED TO JUST 6 % ON ALL
GEN- PRO GEN-SETS

>

ENGINE MODEL (WARRANTY)
HONDA GX390 O.H.V. (3 YEARS)

ENGINE START METHOD
12VDC ELECTRIC & ROPE RECOIL

ENGINE HP @ 3600 RPM
13 HP

ENGINE DISPLACEMENT
1 CYLINDER, 23.7 CU. IN. (390 CC)

ENGINE AIR CLEANER
HEAVY DUTY, LOW PROFILE, DUAL ELEMENT FILTERS

ENGINE FUEL TANK
8 GAL. (30.2 L.) METAL FUEL TANK WITH GAUGE, TWIST-CAP, &
SLOSH VALVE

ENGINE OIL SYSTEM
FORCED SPLASH

LOW OIL PROTECTION
AUTOMATIC ENGINE SHUTDOWN PROTECTION AT LOW OIL LEVEL

db(A) AT 7 METERS
78

3/4 LOAD RUN TIME (HRS)
8.4

FUEL USE, GAL/LTR/HR
0.95 / 3.56

MOTOR START POWER
2 1/2 HP, CODE G ELECTRIC MOTOR

CRANE PICK-UP HOOK

>

OPTIONAL EQUIPMENT : CENTRAL PICK-UP ON TOP OF GEN-SET

2-WHEEL DOLLY KIT

OPTIONAL EQUIPMENT : COMPLETE WITH (2) HANDLES AND
“NEVER GO FLAT” WHEELS

MAINLINE CB

30 AMP, 2 POLE MAGNETIC MAIN LINE CIRCUIT BREAKER

HOUR METER

RUN TIME HOURS, PLUS (3) MAINTENANCE ALERTS: 25 HOUR CHANGE
OIL, 25 HOUR CHANGE OIL FILTER, 25 HOUR SERVICE AIR FILTER

POWER RECEPTACLES

(4) NEMA 5-15R 120 VOLTS, AND (1) L-14-30R 240 VOLTS RECEPTACLES

PROTECTIVE ROLL FRAME

RUGGED 1-1/4” ROUND ROLL FRAME, PROTECTING ENTIRE
GEN-SET

LENGTH, INCHES

31

WIDTH, INCHES

25

HEIGHT, INCHES

27.5

SHIP WEIGHT, LBS.

277

CU. FEET SHIP BOX

20

>

Availability: This product was added to our catalog on Tuesday 16 July, 2013

Steambrite Supply