

>



Model Number: 8055EM

J.E. Adams 8055EM, Replacement Vacuum Motor, 5.7in Diameter

Manufacturer: J.E. Adams

J.E. Adams 8055EM Replacement Vacuum Motor 5.7in Diameter
Specification

- Figures based on a 2" orifice:
- Amp Draw = 7.6
- Hours = 800-1000
- Air Watts = 38.05
- Air Flow (CFM) = 96.1
- Suction (In H2O) = 3.21

How to Change your Motor Brushes

Optional

Press On Vacuum Motor Inlet Tube, Cone, or Horn (suction side) SBMcone15
Esteam 355-405
See Video On Link!

Availability: This product was added to our catalog on Monday 30 January, 2012