# Extech Noise Meter Digital



Model Number: 407730

Extech Noise Meter Digital

Manufacturer: Extech Instuments Corp

Digital Sound Level Meter, 40 to 130 dB Range, Frequency Range 300 to 8000 Hz, A and C Frequency Weighting, Accuracy +/-2.0 dB, Resolution 0.1 dB, Display 2000 Count LCD, Fast/Slow Response Time, Includes Microphone Windscreen, 4 AAA Batteries, Instructions

| | |
|---|---|
| Item | Digital Sound Level Meter |
| dB Range | 40 to 130 |
| Frequency Range (Hz) | 300 to 8000 |
| Frequency Weighting | A and C |
| Accuracy | +/-2 |
| Resolution | 0.1 |
| Display | 2000 Count LCD |
| Response Time | Fast/Slow |

Steambrite Supply

# Extech Noise Meter Digital

Output Jack

Yes

Includes

Microphone Windscreen, 4 AAA Batteries, Instructions

Manufacturers Warranty Length

1 Year

*Availability: This product was added to our catalog on Wednesday 10 February, 2010*

Steambrite Supply