Generators Electrical > Generators-Industrial Portable > Gillette Generator GPE-75EH-3-2 Industrial Portable Generator 6000Watts 208Volts 3Phase 18Amp Honda GX390 13HP Electric Start

Gillette Generator GPE-75EH-3-2 Industrial Portable Generator 6000Watts 208Volts 3Phase 18Amp Honda GX390 13HP Electric Start



Model Number: GPE-75EH-3-2

Gillette Generator GPE-75EH-3-2 Industrial Portable Generator 6000Watts 208Volts 3Phase 18Amp Honda GX390 13HP Electric Start

Manufacturer: Gillette Generator

Gillette Generator GPE-75EH-3-2 Industrial Portable Generator 6000 watts 208 volts 3 Phase 18 Cont Amp Honda GX390 13HP Electric Start

Factory Brochure

GENERATOR MODEL

GPE-75EH

MAX. KW @ 3 PH.
6

PRIME KW @ 3 PH.
5.5

PRIME AMPS @ 208 V.
18

PRIME AMPS @ 240 V.
16

PRIME AMPS @ 480 V.
8

GENERATOR REGULATION

Steambrite Supply

Gillette Generator GPE-75EH-3-2 Industrial Portable Generator 6000Watts 208Volts 3Phase 18Amp Honda GX390 13HP Electric Start

5 % VOLTAGE REGULATION ON SINGLE PHASE GEN-SETS.

FREQUENCY REGULATION
5 %, (3 HERTZ) FREQUENCY REGULATION FROM NAME PLATE RATING

“KLEEN-POWER”™
ELECTRICAL WAVEFORM DISTORTION IS LIMITED TO JUST 6 % ON ALL GEN- PRO GEN-SETS

ENGINE MODEL (WARRANTY)
HONDA GX390 O.H.V. (3 YEARS)

ENGINE START METHOD
12VDC ELECTRIC & ROPE RECOIL

ENGINE HP @ 3600 RPM
13 HP

ENGINE DISPLACEMENT
1 CYLINDER, 23.7 CU. IN. (390 CC)

ENGINE AIR CLEANER
HEAVY DUTY, LOW PROFILE, DUAL ELEMENT FILTERS

ENGINE FUEL TANK
8 GAL. (30.2 L.) METAL FUEL TANK WITH GAUGE, TWIST-CAP, & SLOSH VALVE

ENGINE OIL SYSTEM
FORCED SPLASH

LOW OIL PROTECTION
AUTOMATIC ENGINE SHUTDOWN PROTECTION AT LOW OIL LEVEL

Steambrite Supply

Gillette Generator GPE-75EH-3-2 Industrial Portable Generator 6000Watts 208Volts 3Phase 18Amp Honda GX390 13HP Electric Start

db(A) AT 7 METERS
78

3/4 LOAD RUN TIME (HRS)
8.4

FUEL USE, GAL/LTR/HR
0.95 / 3.56

MOTOR START POWER
2 1/2 HP, CODE G ELECTRIC MOTOR

CRANE PICK-UP HOOK
OPTIONAL EQUIPMENT : CENTRAL PICK-UP ON TOP OF GEN-SET

2-WHEEL DOLLY KIT
OPTIONAL EQUIPMENT : COMPLETE WITH (2) HANDLES AND “NEVER GO FLAT” WHEELS

MAINLINE CB
STANDARD 3 POLE MAG CIRCUIT BREAKER – 20A @ 208V & 240V & 10A @ 480V

HOUR METER
RUN TIME HOURS, PLUS (3) MAINTENANCE ALERTS: 25 HOUR CHANGE OIL, 25 HOUR CHANGE OIL FILTER, 25 HOUR SERVICE AIR FILTER

POWER TAKE OFF
POWER TAKE OFF 4 POSITION TERMINAL STRIP

PROTECTIVE ROLL FRAME
RUGGED 1-1/4” ROUND ROLL FRAME, PROTECTING ENTIRE GEN-SET

Steambrite Supply

Generators Electrical > Generators-Industrial Portable > Gillette Generator GPE-75EH-3-2 Industrial Portable Generator 6000Watts 208Volts 3Phase 18Amp Honda GX390 13HP Electric Start

Gillette Generator GPE-75EH-3-2 Industrial Portable Generator 6000Watts 208Volts 3Phase 18Amp Honda GX390 13HP Electric Start

LENGTH, INCHES
31

WIDTH, INCHES
25

HEIGHT, INCHES
27.5

SHIP WEIGHT, LBS.
277

CU. FEET SHIP BOX
20

Options available for Gillette Generator GPE-75EH-3-2 Industrial Portable Generator 6000Watts 208Volts 3Phase 18Amp Honda GX390 13HP Electric Start :

Shipping Surcharges

+Home Delivery Needs Liftgate Curb Service Because No Forklift On Site With Appointment Delivery Time, Commercial Address But Needs Liftgate Service Because No Forklift or Dock on Site No Appointment Provided, Home Delivery Needs Liftgate Curb Service Because No Forklift On Site (Required) No Appointment Provided, None Commercial Address Forklift / Loading Dock On Site No Appointment Provided.

Availability: This product was added to our catalog on Saturday 27 March, 2021

Steambrite Supply